

## CX-TRK, CX-TRN, CX-TRP AND CX-TRX TRANSFORMERS/RECTIFIER












### FEATURES

- AC AND DC MODELS
- STANDARD MOUNT AND PLUG-IN MODELS
- PLUG-IN MODELS ARE UL/CUL LISTED
- FUSED MODEL FOR ADDITIONAL CIRCUIT PROTECTION
- 3 YEAR WARRANTY

### DESCRIPTION

Camden offers a range of 12VAC to 24VAC standard, plug-in and panel (nipple) mount transformers to support any low voltage system application.

The CX-5024 rectifier is used to convert AC power, for use with DC powered devices.

PANEL (NIPPLE) MOUNT		
 	CX-TRN-2024	24 VAC, 20 VA nipple mount transformer
STANDARD MOUNT		
 	CX-TRX-2012	12 VAC, 20 VA standard mount transformer
	CX-TRX-4024	24 VAC, 40 VA standard mount transformer
 	CX-TRX-5024	24 VAC, 50 VA standard mount transformer
FUSED, STANDARD MOUNT		
 	CX-TRX-2024	24 VAC, 20 VA, fused, standard mount transformer
	CX-TRK-2450	24 VAC, 20 VA, standard mount transformer and AC/DC rectifier
PLUG-IN		
 	CX-TRP-4016	16 VAC, 40 VA plug-in transformer
RECTIFIERS		
	CX-5024	Rectifier, (AC-DC) 50 VA

## SPECIFICATIONS

<b>VOLTAGE:</b>	120V AC 60HZ
<b>DIMENSIONS:</b>	<b>CX-TRN-2024:</b> 2"L x 2 3/8"W x 2 1/4"H (51mm x 60mm x 57mm)
	<b>CX-TRX-2012:</b> 3"L x 2"W x 2 1/8" H (76mm x 51mm x 54mm)
	<b>CX-TRX-4024:</b> 2"L x 2 3/8"W x 2 1/2" H (51mm x 60mm x 64mm)
	<b>CX-TRX-5024:</b> 2 1/8"L x 3 1/8"W x 2 5/16" H (54mm x 80mm x 60mm)
	<b>CX-TRX-2024:</b> 2"L x 2 3/8"W x 2 1/2" H (51mm x 60mm x 64mm)
	<b>CX-TRP-4016:</b> 3 1/2"L x 2 1/2"W x 2 1/8" H (89mm x 64mm x 54mm)
	<b>CX-5024:</b> 1"L x 3/4"W x 1/4" H (25mm x 19mm x 6mm)