



CX-WC17 EQUIPMENT PACKAGE:

- 1 CX-33 Multi-Function Relay
- 2 CM-7536/4 - 36" COLUMN "PUSH TO OPEN" SWITCH
- 3 CM-7536/8B - 36" COLUMN "PUSH TO LOCK" SWITCH
- 4 CM-AF503 - LED ANNUNCIATOR WITH OCCUPIED AND "LOCKED" LABELS.
- 5 CX-MDA - MAGNETIC DOOR CONTACT

ADDITIONAL PARTS REQUIRED BUT NOT INCLUDED WITH THE CX-WC17:

- 6 DOOR OPERATOR - SUPPLIED BY OTHERS
- 7 CX-ED2079 - GRADE2 UNIVERSAL ELECTRIC STRIKE
- 8 CX-PS13 - 12/24 VDC LINEAR POWER SUPPLY
- 9 CX-TRX-4024 - 40VA, 24 VAC TRANSFORMER

SYSTEM OPERATION

CX-WC17 OPERATION:

- A. THE DOOR IS NORMALLY CLOSED AND UNLOCKED.
- B. PRESSING THE EXTERIOR COLUMN 'PUSH TO OPEN' SWITCH OPENS THE DOOR.
- C. ONCE INSIDE AND THE DOOR IS CLOSED, PRESSING THE 'PUSH TO LOCK' COLUMN SWITCH LOCKS THE DOOR, DISABLING THE EXTERIOR 'PUSH TO OPEN' COLUMN AND ILLUMINATES THE EXTERIOR ANNUNCIATOR TO SHOW 'OCCUPIED WHEN LIT' AND INTERIOR ANNUNCIATOR TO SHOW 'LOCKED WHEN LIT'
- D. PRESSING THE INTERIOR 'PUSH TO OPEN' SWITCH UNLOCKS THE DOOR, DEACTIVATES THE ILLUMINATED ANNUNCIATOR AND RESETS THE SYSTEM
- E. IF THE DOOR IS OPENED MANUALLY TO EXIT THE RESTROOM, THE OVERHEAD MAGNETIC CONTACT SWITCH RESETS THE SYSTEM.

CAMDEN DOOR CONTROLS
 2395 Skymark Ave.
 Mississauga, ON Canada
 Tel: (905) 366-3377
 www.camdencontrols.com

L4W 4Y6

NAME	DATE	TITLE:
A.OLISA	MAY-25	WASHROOM BARRIER FREE DOOR CONTROL NORMALLY UNSECURED (CX-WC17)
DRAWN		
CHECKED		
ENG APPR.		
MFG APPR.		
QA		
COMMENTS:		

SIZE	DWG. NO.	REV
B	CX-WC17_RISER.DWG	
SCALE:	N/A	SHEET 1 OF 1