## CX-EMF-2 Multi-Function Relay



Camden's CX-EMF-2 Multi-Function Relay is a microprocessor-controlled relay designed to easily and quickly handle a variety of specialized doorcontrol tasks.

This smart new design allows for future development by utilizing expandable technology and reprogrammable IC 's.

All wiring connections and adjustments are made on the exterior of the plastic case with removable terminals to facilitate installation. Simple yet effective potentiometers enable settings to meet varied requirements.

A power LED, 1 status LED, and five relay LEDs aid in set-up and troubleshooting.

Also available is the option of a metal cabinet with lighted control switches.



Camden's CX-EMF-2 Multi-Function Relay Module is designed to provide the best performance and value in the industry.

## **Features**

- Microprocessor Control
- User Selectable Multi-Application Design
- Plug-in Connectors for Wiring
- Accepts up to 7 Dry Inputs
- 5 Form 'C', 3 Amp Relay Outputs
- 12/24V AC/DC Operation
- 3 Year Warranty



SPECIFICATIONS			
VOLTAGE: CURRENT DRAW:	12/24V AC/DC 150mA @ nominal 500mA @ maximum	ELECTRICAL LIFE:	100,000 operations @ rated or 500,000 operations @ 1/2 rated capacity
RESPONSE TIME: MODE SELECTOR:	<ul> <li>Via 3 dipswitches</li> <li>7 Dry Contacts, 1 Digital Input</li> <li>5 SPDT Relays, 1 Digital Output</li> <li>Version A1-001</li> <li>NG: 3 Amps @ 20 VDC</li> </ul>	MOUNTING:	EMF-2: Double-sided foam tape or (2) #6 screws EMF-2M & EMF-2ABM: 4 x Metal screws & anchors
INPUTS: OUTPUTS:		ENCLOSURE:	EMF-2: Formed Plastic Housing EMF-2M & EMF-2ABM: Beige Metal Cabinet
FIRMWARE: CONTACT RATING: TIME DELAYS:		DIMENSIONS:	EMF-2: 3" W x 7" H x 7/8" D (76 mm x 178 mm x 22 mm) EMF-2M & EMF-2ABM: 7-1/2" W x 12" H x 3-3/4" D (191 mm x 305 mm x 95 mm)

## **ORDERING INFORMATION**



CX-EMF-2 Relay Supplied in Sturdy Gray Plastic Case



Relay Supplied in Lockable Beige Metal Cabinet with Illuminated On/Off Switch for Door Status



Relay Supplied in Lockable Beige Metal Cabinet with Two Illuminated On/Off Switches for Door Status



CX-MDC One Set of Magnetic Door Contacts. Used in Man-Trap and Restroom Door Applications





## **Opening New Doors to** CAMDEN Innovation, Quality and Support! DOOR CONTROLS

5502 Timberlea Blvd. Mississauga, ON Canada L4W 2T7 • Toll Free: 1 877 226-3369 (CAMDEN9) Tel: (905) 366-3377 • Fax: (905) 366-3378 • E-mail: info@camdencontrols.com • www.camdencontrols.com

